

DuroMax

XP28000IH

USER MANUAL



This manual provides information regarding the operation and maintenance of these products. We have made every effort to ensure the accuracy of the information in this manual. We reserve the right to change this product at any time without prior notice.

5800 Ontario Mills Pkwy
Ontario, CA 91764 USA
www.duromaxpower.com

Call our Customer Care Team Toll Free 8-5 PM PST Mon-Fri

844-DUROMAX



CONTENTS

1.	Introduction	
	Introduction	6
	General Safety Procedures	8
	Carbon Monoxide Safety	14
	Unit and Purchase Information	16
2.	Generator Components	
	Generator Components	18
	Package Contents	20
3.	Generator Setup	
	Connect the Battery	22
	Adding Oil	23
	Adding Gasoline	24
	Grounding the Generator	25
	High Altitude Operation	25
4.	Starting the Generator	
	Check the Oil	28
	Check the Gas Level	29
	Starting the Generator Using Gasoline	30
	Starting the Generator Using Propane.....	32
	Starting the Generator Using Remote Start	36
	Starting the Generator Using 2 Wire Start.....	38
5.	Using the Generator	
	AC Usage	42
	Connecting the Generator to a Home.....	45
	Connecting a Load to the Generator.....	46
	Choosing the Right Power Cord	47
	Using the Digital Multimeter	48
	Low Idle Usage	49
	Using the Battery Tender	50
	Using the DC Output	51
	Syncing the Remote	53

6.	Stopping the Generator	
	Shutting Down the Generator On Gasoline.....	56
	Shutting Down the Generator On Propane.....	57
	Shutting Down the Generator With the Remote.....	58
7.	Maintenance and Care	
	Maintenance Schedule.....	60
	Break-In Period	61
	Maintenance Log	61
	Checking the Oil.....	63
	Changing the Oil.....	64
	Cleaning the Air Filter	66
	Spark Plug Maintenance	68
	Transporting the Generator	70
	Storing the Generator for Use Within 30 Days.....	71
	Storing the Generator for Longer than 30 Days	72
	Specifications.....	74
8.	Troubleshooting	
	Basic Troubleshooting	77
9.	Warranty	78
10.	Contact Information	81

For more information and resources on this model scan the QR code below to link to our website product information page.



Duro Max

DuroMax

THE DUROMAX WAY

The DuroMax Way is more than just a brand, it is our understanding and appreciation of just how important power can be to someone without it...



DUROMAX FOR HOME

Electricity in our home not only provides comfort but safety as well. From keeping the heat or A/C on to keeping our food cold, power is essential to our daily lives. Inevitably when disaster strikes and we are left without power for a prolonged period of time, our way of life is put at risk. This is by far the most critical time for reliable portable power.



DUROMAX FOR WORK

On the job site, portable power allows you the ability to get work done in remote locations when traditional power sources are usually unavailable. Equipment like table saws, sanders, and work lights are a necessity and portable power can play a critical role in getting a job done successfully and efficiently.



DUROMAX FOR PLAY

Camping outdoors in a remote location can get one in touch with nature and allow them to forget the stress of the day to day grind. Here portable power can provide comfort as well as safety. With portable power, you can keep your cell phone charged, light up your campsite, or even brew a cup of coffee, all while being miles from civilization.

The DuroMax Way is a commitment to excellence. This vision is focused on the quality, reliability, and durability of our products combined with outstanding customer service. We understand that having dependable power whenever and wherever you need it provides comfort, safety, and peace of mind. It is through this philosophy that DuroMax achieves our vision of...

POWERING EVERYONE... *ANYWHERE!*

INTRODUCTION

DuroMax Power Equipment is headquartered in Ontario, California and is the industry's leader in Dual Fuel and Tri Fuel portable generator technology. In addition to a full assortment of portable generators ranging from digital inverters to large 28,000-watt generators that can power your whole home, their product line includes power stations, pressure washers, engines, pumps, and accessories.

The foundation of our company is built on quality, reliability, durability, and customer service. At DuroMax our vision is simple, we are committed to Powering Everyone... Anywhere!



Notice Regarding Emissions

Engines that are certified to comply with U.S. EPA emission regulations for SORE (Small Off-Road Equipment), are certified to operate on regular unleaded gasoline and may include the following emission control systems: (EM) Engine Modifications and (TWC) Three-Way Catalyst (if so equipped).

GENERAL SAFETY PROCEDURES



SAFETY ALERT SYMBOL

The safety alert symbol is used with one of the safety words (**DANGER**, **WARNING**, or **CAUTION**) to alert you of hazards. Please pay attention to these hazard notices both in this manual and on the engine.

Please familiarize yourself with the following safety symbols and words:

- **DANGER**: Indicates a hazard that will result in serious injury or death if instructions are not followed.
- **WARNING**: Indicates a strong possibility of causing serious injury or death if instructions are not followed.
- **CAUTION**: Indicates a possibility of personal injury or equipment damage if instructions are not followed.



DANGER: This generator produces poisonous carbon monoxide gas when running. This gas is both odorless and colorless. Even if you do not see or smell gas, carbon monoxide may still be present. Breathing this poison can lead to headaches, dizziness, drowsiness, and eventually death.

- Use outdoors **ONLY** in non-confined areas.
- Keep several feet of clearance on all sides to allow proper ventilation of the generator.



WARNING: The exhaust from this product contains chemicals known to the State of California to cause cancer, birth defects, or other reproductive harm.



WARNING: This generator produces heat when running. Temperatures near exhaust can exceed 150°F (65°C).

- Do not touch hot surfaces. Pay attention to warning labels on the generator denoting hot parts of the machine.
- Allow generator to cool several minutes after use before touching engine or areas which heat during use.



WARNING: This generator may emit highly flammable and explosive gasoline vapors, which can cause severe burns or even death. A nearby open flame can lead to an explosion even if not directly in contact with gasoline.

- Do not operate near an open flame.
- Do not smoke near the generator.
- Always operate on a firm, level surface.
- Always turn the generator off before refueling.
- Allow generator to cool for at least 2 minutes before removing the fuel cap. Loosen cap slowly to relieve pressure in the tank.
- Do not overfill the gas tank. Gas may expand during operation. Do not fill to the top of the tank.
- Always check for spilled gas before operating.
- Empty the gasoline tank before storing or transporting the generator.
- Before transporting, turn the fuel valve to the off position and disconnect the spark plug.



WARNING: This generator produces a powerful voltage, which can result in electrocution.

- ALWAYS ground the generator before using it (see the “Grounding the Generator” portion of the “PREPARING THE GENERATOR FOR USE section).
- The generator should only be plugged into electrical devices, either directly or with an extension cord. NEVER connect to a building electrical system without a qualified electrician. Such connections must comply with local electrical laws and codes. Failure to comply can create a back-flow of power, which may result in serious injury or death to utility workers.
- Use a ground fault circuit interrupter (GFCI) in highly conductive areas such as metal decking or steelwork. GFCIs are available in-line with some extension cords.
- Do not use uncovered in rainy or wet conditions.
- Do not touch bare wires or receptacles (outlets).
- Do not allow children or non-qualified persons to operate.

Duro Max

Button/Coin Battery Warnings

WARNING

INGESTION HAZARD

This product contain a button cell or coin battery

MODEL:
3V CR2032



This symbol means:

INGESTION HAZARD:

This product contains a button cell or coin battery.

1. Remove and immediately recycle or dispose of used batteries according to local regulations and keep away from children. Do NOT dispose of batteries in household trash or incinerate.
2. Even used batteries may cause severe injury or death.
3. Call a local poison control center for treatment information.
4. Non-rechargeable batteries are not to be recharged.
5. Do not force discharge, recharge, disassemble, heat above (manufacturer's specified temperature rating) or incinerate. Doing so may result in injury due to venting, leakage or explosion resulting in chemical burns.
6. Ensure the batteries are installed correctly according to polarity (+ and -).
7. Do not mix old and new batteries, different brands or types of batteries, such as alkaline, carbon-zinc, or rechargeable batteries.
8. Remove and immediately recycle or dispose of batteries from equipment not used for an extended period of time according to local regulations.
9. Always completely secure the battery compartment. If the battery compartment does not close securely, stop using the product, remove the batteries, and keep them away from children.

GENERAL SAFETY PROCEDURES (CONTINUED)

In addition to the above safety notices, please familiarize yourself with the safety and hazard markings on the generator.

⚠ DANGER

Using a generator indoors CAN KILL YOU IN MINUTES.
Generator exhaust contains carbon monoxide. This is a poison you cannot see or smell.

	
NEVER use inside a home or garage, EVEN IF doors and windows are open.	Only use OUTSIDE and far away from windows, doors, and vents.

Avoid other generator hazards.
READ MANUAL BEFORE USE

AUTOMATIC SHUTOFF

If your generator has shut off/shutoff and the CO Alert RED indicator light appears on the front panel, the unit has detected an excessive amount of carbon monoxide in the air. Follow the following directions **BEFORE** attempting to restart your generator:
Please consult your owner's manual for additional information.

ONLY OPERATE GENERATOR IN AN OPEN, OUTDOOR AREA AT LEAST 5 FEET AWAY FROM ANY FLAMMABLE MATERIAL. POINT EXHAUST AWAY FROM STRUCTURES. DON'T RUN GENERATORS IN ENCLOSED AREAS (I.E. NOT IN HOUSE OR GARAGE).



⚠ WARNING TAMPERING WITH THE CO-ALERT SENSOR WILL DISABLE THE GENERATOR.





CARBON MONOXIDE SAFETY

Carbon Monoxide



Generators are convenient, but they can also be dangerous. All fuel-burning appliances and equipment release a poisonous gas called carbon monoxide.

Carbon monoxide (also known as CO) can be dangerous for humans and pets, even in small amounts, because it blocks oxygen from getting into your body. Carbon monoxide poisoning can lead to death in a very short time. It is odorless, tasteless and invisible, so you may be exposed without knowing it. That is why carbon monoxide is sometimes called “the silent killer.”

CO ALERT



Description

The DuroMax CO ALERT system was created to protect our customers and their families from dangerous carbon monoxide. Just like the detector for your home the CO ALERT tests the air for to keep you safe and healthy.



CO Detected

If dangerous carbon monoxide levels are detected:

- The indicator will light red.
- The engine will shutdown.
- The engine will not restart for 5 minutes.



Maintenance Required

If an error in the CO ALERT system is detected the indicator will light yellow. Please contact DuroMax service at 844-DUROMAX for assistance.



**ALWAYS READ THE
OWNER'S MANUAL FIRST**

KNOW THE SYMPTOMS

- HEADACHE
- NAUSEA
- SHORTNESS OF BREATH
- DIZZINESS
- FATIGUE




**IF YOU FEEL SYMPTOMS,
LEAVE RIGHT AWAY**

**STAY ALERT WITH CARBON
MONOXIDE DETECTORS**



**POINT FUMES AWAY
FROM NEARBY PEOPLE**

**KEEP IT OUTSIDE AND AWAY
FROM DOORS AND WINDOWS**



PGMA
Portable Generator Manufacturers Association

As the only safe way to use a portable generator, taking your generator outside is absolutely mandatory to keep your family safe from carbon monoxide. But there's even more you can do. By educating yourself about all carbon monoxide risks, you'll be better prepared to protect your family from this colorless, odorless threat. Visit takeyourgeneratoroutside.com for more information.

**TAKE IT
OUTSIDE™**



CARBON MONOXIDE KILLS


UNIT AND PURCHASE INFORMATION

Serial Number



Serial number

The serial number is located on the left service panel main sticker and on the lower portion of the sticker.



Serial number format

The serial number will be shown in two parts. The engine model, followed by the serial number.

Engine Model: _____

Serial Number: _____

STAPLE RECEIPT HERE

A purchase receipt may be necessary for warranty parts or service in the future. If you have a paper receipt, staple it here for easy reference.

If you purchased the unit online, save the email receipt where you can access it, and record your details here for convenience in the future.

Purchase Date: _____

Order Number: _____

Retailer Name: _____




GENERATOR COMPONENTS

To help you get familiar with your new DuroMax generator, please see this component section for easy reference on all the generator's individual features.

GENERATOR COMPONENTS



1. **Wheels** - Solid wheels allow for easy transportation over any terrain.
2. **Handles** - Allow for easy steering during transportation.
3. **Power Panel** - Contains the start switch, plugs, meters, and circuit breakers.
4. **Fuel Tank** - All metal 12.7 gallon gasoline fuel tank.
5. **Brake** - A wheel brake to lock the generator in place.
6. **Right Maintenance Cover** - This maintenance cover allows easy access to the battery, spark plug, oil fill, oil drain, and air filter.
7. **LPG Inlet** - Connects the LPG inlet to the LPG hose/regulator.
8. **Battery Tender** - Easily keep your battery charge when the generator is in storage by using the included 120V battery charger.
9. **Fuel Selector** - GAS/LPG knob that changes the fuel into the engine.
10. **Low Idle** - Lowers the engine speed to match the load to save on fuel and reduce noise levels.
11. **Start Button** - Starts and shuts down the generator.
12. **Start Up Switch** - Allows power to the starter and panel. Prevents accidental starting.



- 13. **Multimeter** - Provides information of Hours Run, Voltage, Hertz, CO PPM, and Load on the generator measured in kW.
- 14. **30A Breaker** - Protects the 30A outlet from an overload or short circuit.
- 15. **DC Output** - Allows you to charge your lithium ion 48V-58V batteries.
- 16. **Main Breaker** - Protects the full panel from an overload or short circuit.
- 17. **50A Breakers** - Protects the 50A outlets from an overload or short circuit.
- 18. **240V 50A Outlets** - Use to connect electrical devices that run 120 or 240 volt, 60 Hz, single-phase, AC current (NEMA 14-50).
- 19. **240V 30A Outlet** - Use to connect electrical devices that run 120 or 240 Volt, 60 Hz, single-phase, AC current (NEMA L14-30).
- 20. **120V GFCI Outlets** - Use to connect electrical devices that run 120 volt, 60 Hz, single-phase, ac current (NEMA 5-20).
- 21. **CO Alert** - Shuts down the engine in the event of CO buildup.
- 22. **2 Wire Start** - Used to start the generator through an external controller.

PACKAGE CONTENTS

Your generator comes with the items listed below. Please check to see that all of the following items are included with your generator.



Double Sided Screw Driver

Phillips and slot blade screwdriver used for generator maintenance.



Socket Wrench

An 8mm socket wrench used for generator maintenance.



Spark Plug Wrench

Used in spark plug maintenance, inspection, and installation.



Oil Funnel w/ Hose

Used to add oil to the generator without messy spills.



Battery Tender

Used to charge the battery when in storage



Remote Control

Used to remotely start the generator.



Propane Regulator w/ Hose

Used to provide a regulated propane supply to the propane inlet.



DC Output Wires

Used to charge 48-52V DC batteries.

- Note: Actual tools may differ in appearance or design from image shown.



GENERATOR SETUP

Proper setup of your generator will get you going as soon as possible while making sure you and your equipment are safe and cared for.


GENERATOR SETUP (CONTINUED)

Step 1 - Connect the Battery




1. Remove right service cover

- a. Remove the right maintenance cover using the socket wrench from the toolkit.



2. Locate the negative cable

- a. Locate the negative battery cable above and behind the battery. One side is connected to ground and the other end needs to be connected to the battery.
- b. Route the free end to the negative battery terminal.



3. Connect the negative cable

- a. Push the black rubber boot up the wire to expose the connector.
- b. Securely connect the free end of the battery cable to the negative battery terminal using the screw and nut from the battery with the screwdriver and wrench from the toolkit.



4. Reinstall the service cover

- a. Cover the connected terminal with the black rubber boot.
- b. Reinstall the service cover using the socket wrench from the toolkit.


Step 2 - Adding Oil

The generator requires engine oil to operate properly. The generator, when new from the package, contains no oil in the crankcase*. You must add the proper amount of oil before operating the generator for the first time. This amount is equal to the oil capacity of the engine crankcase:

Model Number	XP28000iH
Engine Oil Capacity	84.5 fl. oz. (2.5 L)



WARNING: Do not apply engine oils with additives or 2-stroke gasoline engine oils; they don't have enough lubrication and may shorten the engine's service life.



Engine oil recommended: SAE 10W-30.

Viscosity varies with regions and temperatures. Choose your oil viscosity using the chart to the left.

* A small amount of oil from factory testing may be present on arrival.

* Synthetic oil may be used after the 8 hour initial break-in period. Using synthetic oil does not increase the recommended oil change interval. Full synthetic 5W-30 oil will aid in starting in cold temperatures <5°C (41°F).

Add oil

- Make sure the generator is on a level surface.
- Remove oil maintenance side panel.
- Remove oil fill cap.
- Using a funnel, add the appropriate amount of oil into the crankcase. You can check the oil level of the generator with the dipstick. Simply pull the dipstick and the indicated oil level is on the end of the stick.
- Replace oil filler cap.



WARNING: Do not overfill the crankcase. This may damage the motor and shorten the overall life of your generator.



GENERATOR SETUP (CONTINUED)

Step 3 - Adding Gasoline (Optional)



Add gasoline

- Make sure the generator is on a level surface.
- Unscrew gas cap and set aside (NOTE: the gas cap may be tight and hard to unscrew).
- Slowly add unleaded gasoline to the fuel tank. Be careful not to overfill. The fuel gauge on the top of the gas tank indicates how much gasoline is in the generator gas tank.
- Replace fuel cap and wipe up any spilled gasoline with a dry cloth.

Model Number	XP28000iH
Gas Tank Capacity	12.7 US gal. (48 L)



WARNING: Gas can expand. Do not fill the gas tank to the very top. Leave a minimum of 1.5 in open space. Gasoline and gas fumes are highly flammable. Do not fill the tank near an open flame. Always check for fuel spills.

IMPORTANT:

- To ensure that the generator runs smoothly use only FRESH, UNLEADED GAS WITH AN OCTANE RATING OF 87 OR HIGHER.
- Never use an oil/gasoline mixture. Never use old gas.
- Avoid getting dirt or water in the fuel tank.
- Gas can age in the tank and make it hard to start up the generator in the future.
- Never store generator for extended periods of time with fuel in the tank.

Step 4 - Grounding the Generator



Attach grounding wire

- Ground the generator by tightening the grounding nut against a grounding wire.
- Connect the other end to a copper or brass grounding rod that's driven into the earth.

A generally acceptable grounding wire is a No. 12 AWG (American Wire Gauge) stranded copper wire.

Grounding codes can vary by location. Please contact a local electrician to check the grounding regulations for your area.

Note: If the generator is connected to a home, then it won't be necessary to attach the separate grounding wire and you can opt to use your home ground instead. Please see a certified electrician for further options with grounding your generator.



WARNING: Failure to properly ground the generator can result in electrocution.

High Altitude Operation

At high altitudes, the standard carburetor air/fuel mixture will be too rich. The performance will decrease, and fuel consumption will increase. A very rich mixture will also foul the spark plug and cause hard starting. Operation at an altitude that differs from that at which this engine was certified, for extended periods of time, may increase emissions. High altitude performance can be improved by specific modifications to the carburetor. If you always operate your generator at altitudes above 3,000 feet (900 meters), have a dealer perform this carburetor modification. This engine, when operated at high altitude with the carburetor modifications for high altitude use, will meet each emission standard throughout its useful life. Even with carburetor modification, engine horsepower will decrease by about 3.5% for each 1,000-foot (300-meter) increase in altitude. The effect of altitude on horsepower will be greater than this if no carburetor modification is made.

When the carburetor has been modified for high altitude operation, the air/fuel mixture will be too lean for low altitude use. Operation at altitudes below 3,000 feet (900 meters) with a modified carburetor may cause the engine to overheat and result in serious engine damage.

Duro Max



STARTING THE GENERATOR

If this is not your first time using the generator there are still steps you should take to prepare it for operation each time you use it.

IMPORTANT: At this point, you should be familiar with the procedures described in the first portion of this section entitled “GENERATOR SETUP” If you have not yet read this section, go back and read it now.

BEFORE YOU START YOUR GENERATOR

Step 1 - Check the Oil



Check the oil

The generator is equipped with an automatic shutoff to protect it from damage due to low oil; nonetheless, you should check the oil level of the engine before each use to ensure that the engine crankcase has a sufficient amount.

To check the oil level:

- a. Make sure the generator is on a level surface.
- b. Pull out dipstick.
- c. With a dry cloth, wipe the oil off of the dipstick.
- d. Insert the dipstick as if you were replacing it and then remove it again. There should now be oil on the stick. If there is no oil on the stick, or oil only at the very end of the stick, you should add oil until the engine crankcase is filled (see “Adding Oil” portion of the “Maintenance” section).
- e. Be sure to replace the dipstick when finished checking oil.

Model Number	XP28000iH
Engine Oil Capacity	84.5 fl. oz. (2.5 L)

Step 2 - Check the Gas Level (Optional)



Check fuel level

If running the engine on gasoline, check to see that there is sufficient gasoline in the fuel tank. The fuel gauge on top of the tank will give a rough estimate of the gasoline level. The gauge will appear white then fill red as the tank is filled.

Note: Fuel gauge may not register with less than 1/3 fuel tank full.



WARNING: Gasoline and gasoline fumes are highly flammable.

- Do not fill the tank near an open flame.
- Always allow the engine to cool for several minutes before refueling.
- DO NOT overfill the fuel tank. Fuel expands when shaken or heated. ALWAYS leave 1½" space or more at the top of the tank.
- ALWAYS use fresh fuel or stabilized fuel. Old gasoline (older than 30 days) can cause permanent damage to the fuel system.
- Always check for fuel spills.


STARTING THE GENERATOR

Starting the Generator Using Gasoline



1. Select GAS fuel

The fuel selector is located on the top left corner of the front power panel. Rotate the fuel selector knob clockwise to select GAS as a fuel source.



2. Flip main breaker OFF

The main breaker is located on the top right corner of the front power panel. Flip the breaker OFF to prevent an accidental load when starting the generator.



3. Flip low idle OFF

The low idle is located on the left side of the front power panel and next to the fuel selector knob. Flip the switch down to disable low idle when starting the generator.



4. Flip 2 wire start switch OFF

The 2 wire start switch is located on the left side of the front power panel next to the fuel inlet. Flip the 2 wire switch down to the OFF position.



5. Flip start switch ON

The start switch is located on the left side of the front power panel next to the control center. Press the switch up to the ON position to allow the generator to start.



6. Press the START button

The start button is located on the left side of the power panel. Press the button down for 1-3 seconds to start the generator.



7. Flip main breaker ON

The breaker is located on the top right corner of the front power panel. Flip the breaker ON to allow the power to flow to the receptacles.



CAUTION: Disconnect all electrical loads from the generator before attempting to start!

STARTING THE GENERATOR (CONTINUED)

Starting the Generator Using Propane




1. Connect propane hose

The LPG inlet is located on the bottom left corner of the front panel. Connect the propane hose to both the inlet and the propane tank. Open the propane tank.



2. Select LPG fuel

The fuel selector is located on the top left corner of the front power panel. Rotate the fuel selector knob clockwise to select LPG as a fuel source.



3. Flip main breaker OFF

The main breaker is located on the top right corner of the front power panel. Flip the breaker OFF to prevent an accidental load when starting the generator.



4. Flip low idle OFF

The low idle is located on the left side of the front power panel and next to the fuel selector knob. Flip the switch down to disable low idle when starting the generator.



5. Flip 2 wire start switch OFF

The 2 wire start switch is located on the left side of the front power panel next to the fuel inlet. Flip the 2 wire switch down to the OFF position.



6. Flip start switch ON

The start switch is located on the left side of the front power panel next to the control center. Press the switch up to the ON position to allow the generator to start.



7. Press the START button

The start button is located on the left side of the power panel. Press the button down for 1-3 seconds to start the generator.



8. Flip main breaker ON

The breaker is located on the top right corner of the front power panel. Flip the breaker ON to allow the power to flow to the receptacles.

Duro Max

STARTING THE GENERATOR (CONTINUED)

Starting the Generator Using Propane (Continued)



WARNING: WHEN USING THE GENERATOR WITH LPG, MAKE SURE THERE IS NO POSSIBLE IGNITION SOURCE CLOSE TO THE GENERATOR.

1. Before using, make sure all of the LPG connectors and hoses are well connected and sealed.
2. Connect electrical devices to the generator ONLY after the engine runs smoothly. (There may be remnant gasoline in the carburetor; and this can cause unsteady engine performance for several minutes)
3. If the propane gas leaks, shut off the LPG supply first and then quickly unplug or turn off any electrical devices powered by the unit.
4. When stopping the engine, unplug or turn off any electrical devices, turn off the main circuit breaker and then turn off the LPG supply. After the engine has stopped turn the battery switch to the "OFF" position.



CAUTION: Disconnect all electrical loads from the generator before attempting to start!

Propane Requirements



CAUTION: Always use the provided propane hose and regulator supplied with your generator. Failure to use the supplied regulator can damage your generator and void your warranty.

Note: Required fuel pressure to provided propane hose and regulator at all load ranges needs to be a minimum of 3 PSI.

Model Number	XP28000iH
Minimum Recommended Propane Tank Size	60 lbs.
BTU/Hr at Full Load	418,000 BTU/Hr


STARTING THE GENERATOR (CONTINUED)

Starting the Generator Using Remote Start



1. Select fuel

The fuel selector is located on the left side of the front power panel. If using propane rotate the fuel selector knob to LPG, connect propane hose, and turn on propane source. If using gasoline rotate the fuel selector knob to GAS.



2. Flip main breaker ON

The main breaker is located on the top right corner of the front power panel. Flip the breaker ON to allow the power to flow to the receptacles.



3. Flip low idle OFF

The low idle is located on the left side of the front power panel and next to the fuel selector knob. Flip the switch down to disable low idle when starting the generator.



4. Flip 2 wire start switch OFF

The 2 wire start switch is located on the left side of the front power panel next to the fuel inlet. Flip the 2 wire switch down to the OFF position .



5. Flip start switch ON

The start switch is located on the left side of the front power panel next to the control center. Press the switch up to the ON position to allow the generator to start.



6. Push the START button

The remote start has two buttons, START and STOP. Press the START button two times in succession to start the generator. Hold the STOP button to shut the generator off.


STARTING THE GENERATOR (CONTINUED)

Starting the Generator Using 2 Wire Start



1. Select fuel

The fuel selector is located on the left side of the front power panel. If using propane rotate the fuel selector knob to LPG, connect propane hose, and turn on propane source. If using gasoline rotate the fuel selector knob to GAS.



2. Flip main breaker ON

The main breaker is located on the top right corner of the front power panel. Flip the breaker ON to allow the power to flow to the receptacles.



3. Flip low idle OFF

The low idle is located on the left side of the front power panel and next to the fuel selector knob. Flip the switch down to disable low idle when starting the generator.



4. Flip 2 wire start switch ON

The 2 wire start switch is located on the left side of the front power panel next to the fuel inlet. Flip the 2 wire switch up to the ON position .



5. Flip start switch OFF

The start switch is located on the left side of the front power panel next to the control center. Press the switch down to the OFF position.



6. Connect 2 wire start

Connect the 2 wire start cord to the 2 wire outlet port. The generator will now automatically start with the appropriate 2 wire start signal.

Duro Max



USING THE GENERATOR

If this is not your first time using the generator, there are still steps you should take to prepare it for operation each time you use it.

IMPORTANT: At this point, you should be familiar with the procedures described in the first portion of this section entitled “GENERATOR SETUP”; if you have not yet read this section, go back and read it now.

AC Usage

- You may connect electrical devices running on AC current according to their wattage requirements.
- The chart below shows the rated and surge wattage of your generator according to its model number.
- The rated wattage corresponds to the maximum wattage the generator can output on a continuous basis.
- The surge wattage corresponds to the maximum amount of power the generator can output for a short period of time. In addition to the rated wattage listed by the device, many electrical devices such as refrigerators require short bursts of extra power to stop and start their motors. The surge wattage ability of the generator covers this extra power requirement.

Fuel Source	Rated (Running) Wattage	Surge (Peak) Wattage
Gasoline	22000	28000
Propane	20000	25000

The total running wattage requirement of the electrical devices connected to the generator should not exceed the rated wattage of the generator itself. To calculate the total wattage requirement of the electrical devices you wish to connect, find the rated (or running) wattage of each device. This number should be listed somewhere on the device or in its instruction manual.

If you cannot find this wattage, you may calculate it by multiplying the voltage requirement by the amperage drawn: $\text{watts} = \text{volts} \times \text{amps}$. If these specifications are not available, you may estimate the watts required by your device by using the chart on the next page.

Once you have found the rated wattage requirement of each electrical device, add these numbers to find the total rated wattage you wish to draw from the generator. If this number exceeds the rated wattage of the generator, DO NOT connect all these devices. Select a combination of electrical devices, which has a total rated wattage lower than or equal to the rated wattage of the generator.

Tool or Appliance	Rated (Running) Watts	Additional Surge Watts
Electric water heater (40 gal)	4000	0
Hot plate	2500	0
Radial arm saw	2000	2000
Electric stove	1500	0
Circular saw	1500	1500
Air compressor (1 HP)	1500	3000
Window air conditioner	1200	1800
Miter saw	1200	1800
Microwave	1000	2000
Well water pump	1000	1500
Reciprocating saw	960	1040
Sump pump	800	1200
Refrigerator freezer	800	1200
Furnace blower	800	1300
Computer	800	0
Electric drill	600	900
Television	500	0
Deep freezer	500	800
Garage door opener	480	600
Stereo	400	0
Box fan	300	600
Clock radio	300	0
Security system	180	0
DVD player	100	0
Common light bulb	75	0



CAUTION: The generator can only run at its surge wattage capacity for a very short time. Connect only electrical devices requiring a rated (running) wattage equal to or less than the rated wattage of the generator. Never connect devices requiring a rated wattage equal to the surge wattage of the generator.

*NOTE: The above wattage figures are estimates only.
Try to check the wattage listed on your electrical devices before consulting this chart.*



XP16000iH Used For Reference

USING THE GENERATOR (CONTINUED)

Connecting the Generator to a Home



Interlock kit

- Choose what circuits you want to run.
- Requires an electrician to install, but you have the flexibility of switching up your circuits depending on your power needs.
- More hands-on, and some electrical knowledge is needed so you don't overload the generator.



Transfer switch

- Automatically switches power over to your generator during an outage. Requires an electrician to install.
- Once you choose which circuits you want to power, you're locked into your configuration.



Extension cords

- The most straightforward and affordable option.
- Zero commitment, no installation needed: Simply plug in your appliances and go!
- Perfect for renters, RV/camping trips, and power on the job-site.

USING THE GENERATOR (CONTINUED)

Connecting a Load to the Generator

NOTE: Be sure to attach devices to the correct receptacle (outlet).

- 120V devices can be directly connected to the 120V ONLY receptacles.
- 120V devices can be connected to the 120/240V receptacle using an appropriate adapter.
- 240V devices can ONLY be connected to the 240V receptacle.



CAUTION: Do not connect 50 Hz or 3-phase loads to the generator.



1. Plug in devices

Plug in devices to the appropriate receptacle. When using the generator, balance the load as closely as possible. Placing more load on one side of the circuit will reduce the breaker trip period.



2. Flip main breaker ON

Flip the circuit breaker up to the ON position to allow power to the receptacles.



3. Turn on connected devices

Start or turn on appliances, starting with the biggest loads first.

Choosing the Right Power Cord

Long or thin cords can drain the power provided to an electrical device by the generator. When using such cords, allow for a slightly higher rated wattage requirement for the electrical device. See the table below for recommended cords based on the power requirement of the electrical device.


DEVICE REQUIREMENTS		WIRE GAUGE BY LENGTH (ft.)				
AMPS	WATTS (120/240V)	10	25	50	100	150
5	600/1200	18	16	14	12	10
10	1200/2400	16	14	12	12	10
15	1800/3600	14	14	12	12	10
20	2400/4800	12	12	12	10	10
25	3000/6000	12	10	10	10	8
30	3600/7200	10	10	10	8	NR
40	4800/9600	8	8	6	6	NR
50	6000/12000	6	6	6	NR	NR
*NR = NOT RECOMMENDED		*Gauge based on twisted copper wire				

From home back up to just running your electric edger and everything in-between DuroMax has the power cord for you. All DuroMax cords are 100% twisted copper wire for maximum life and reliability.

Length	120V 15A					240V 30A	240V 50A
	14 Gauge	12 Gauge		10 Gauge			6 Gauge
	Single Outlet	Single Outlet	Triple Outlet	Single Outlet	Triple Outlet	L14-30P/ L14-30R	14-50P/ CS6364
10 ft						XP3010GC	
15 ft							XP5015GC
25 ft	XPC14025A	XPC12025A	XPC12025C	XPC10025A	XPC10025C	XP3025GC	XP5025GC
50 ft			XPC12050C	XPC10050A	XPC10050C	XP3050GC	XP5050GC
100 ft		XPC12100A	XPC12100C	XPC10100A	XPC10100C		

USING THE GENERATOR (CONTINUED)

Using the Digital Multimeter



1. **Runtime/Total Hours** - This portion of the display will automatically switch between the current runtime and total runtime hours of the unit.
2. **Voltage** - This portion of the display will show the voltage output of the generator.
3. **Load** - This portion of the display shows the current load output in kW.
4. **CO PPM** - This portion of the display shows the current CO content in the air measured in PPM.
5. **Frequency** - This portion of the display shows the frequency output of the generator.

Low Idle Usage



Low Idle

The low idle feature automatically lowers the RPM of the generator based on the current load to help conserve fuel and lower the noise of the generator.

Turn on the low idle for better fuel efficiency and to make the generator quieter.



CAUTION: Some high surge items may not work correctly with low idle.

USING THE GENERATOR (CONTINUED)


Using the Battery Tender



The generator battery can steadily lose charge during longer periods of storage. Plug the provided trickle charger in to ensure your battery is maintained and ready for use if needed.



CAUTION: Avoid allowing the 12V battery to drop below 11.6V of charge, this can cause permanent damage to the battery cells.



Connect the battery tender

- The battery tender outlet is located to right the start switch. Connect the battery tender cord to the battery tender outlet.
- Connect the other end of the battery tender to a standard 120V wall outlet.


Using the DC Output



The DC output can be used to help recharge 48V-58V lithium ion batteries for various applications. **NOTE: The power used on the DC output will be deducted from the total available AC power on the panel.**



CAUTION: Always disconnect the DC output charger before turning the generator off to avoid damaging the internal inverter.



Connect the DC output to external battery

- Start the generator
- Connect the provided DC output leads to the DC output ports.
- Connect the other end of the DC output leads to the 48V-52V lithium ion battery terminals to charge.



CAUTION: The DC charger will maintain a constant output. Always disconnect the lithium ion battery once it is fully charged to avoid overcharging the battery.

Duro Max

USING THE GENERATOR (CONTINUED)

Syncing the Remote



1. Flip start up switch ON

Flip the start up switch to the ON position to allow power to the panel.



2. Engage sync mode

Press the start button 5 times within 2 seconds. The start button turns red to indicate that it has entered the sync mode.



3. Press start button on remote

Press the start button on the remote control. The start button flashes once to indicate that the syncing is successful. If you have additional remote controls, press the start button for each one to add to sync.



4. Disengage sync mode

After adding all desired remotes, press the start button 5 times within 2 seconds to disengage sync mode.

Duro Max




STOPPING THE GENERATOR

This section will cover the recommended shut off procedure for stopping the generator on various fuels.

STOPPING THE GENERATOR

Shutting Down the Generator On Gasoline



1. Flip the main breaker OFF

Move the main breaker to the OFF position.




2. Run the generator

Allow the generator to run for 3-5 minutes.



3. Hold push button to stop


Hold push button for 3 seconds to shut the generator down.



4. Turn battery switch OFF

Turn the battery switch to the OFF position.

Shutting Down the Generator On Propane



1. Turn OFF the main breaker

Move the main breaker to the OFF position.




2. Run the generator

Allow the generator to run for 3-5 minutes.



3. Hold push button to stop

Hold push button for 3 seconds to shut the generator down.




4. Turn battery switch OFF

Turn your propane tank valve to the CLOSE position and shut the battery switch OFF.

STOPPING THE GENERATOR (CONTINUED)

Shutting Down the Generator With the Remote



1. Turn OFF the main breaker

Move the main breaker to the OFF position.




2. Run the generator

Allow the generator to run for 3-5 minutes.



3. Hold the stop button

Hold the STOP button to shut off the generator.



4. Turn start switch OFF

Turn the start switch to the OFF position.



MAINTENANCE AND CARE

Proper maintenance and storage of your generator are essential to ensure trouble-free use of your generator when you need it.

By following the maintenance and care requirements, you can keep your generator running smoothly and efficiently for years to come.

MAINTENANCE AND CARE

Proper routine maintenance of your generator is essential for safe, economical, and trouble-free operation. It will also help reduce air pollution.



WARNING: Improper maintenance, or failure to correct a problem before operation, can cause a malfunction in which you can be seriously injured or killed. Always follow the inspection, maintenance recommendations, and schedules in this instruction manual.

- Make sure the engine is off before you begin any maintenance or repairs.
- Let the engine and exhaust system cool before touching.
- To reduce the possibility of fire or explosion, be careful when working around gasoline. Use only a nonflammable solvent, not gasoline, to clean parts. Keep cigarettes, sparks, and flames away from all fuel-related parts.

Maintenance Schedule

Remember that this schedule is based on the assumption that your machine will be used for its designed purpose. Sustained high-load, high-temperature operation, or use in unusually wet or dusty conditions, will require more frequent service.

SERVICE	EVERY USE	1ST MO. OR 8 HRS. (BREAK IN)	EVERY 3 MO. OR 50 HRS. OF HEAVY USE	EVERY 6 MO. OR 100 HRS. OF NORMAL USE	EVERY 12 MO. OR 300 HRS.	EVERY 3 YRS. OR 500 HRS.
ENGINE OIL	CHECK	CHANGE	CHANGE	CHANGE		
OIL FILTER			CHANGE	CHANGE		
AIR CLEANER	CHECK	CHECK	CHANGE	CHANGE		
SPARK PLUG			CLEAN / ADJUST	CLEAN / ADJUST		
SPARK ARRESTOR	CHECK				CLEAN	
IDLE SPEED					CHECK / ADJUST	
VALVE CLEARANCE					CHECK / ADJUST	
FUEL TUBE	CHECK				CHECK / REPLACE	
FUEL TANK / FILTER					CLEAN	
COMBUSTION CHAMBER						CLEAN

Break-In Period

As the best practice for any new combustion motor it's recommended to perform the break in procedure as follows:

- Run the generator for the first 6-8 hours on conventional oil, then change the oil. After the break-in period synthetic oil may be used.
- During the break in period of the first 6-8 hours keep the generator load under 50% for optimal results.
- Check and clean the air filter if necessary after the break-in period.


Maintenance Log

As a best practice it's recommended to keep a log of the generator hours and maintenance to ensure your generator is always operating to its full potential.

Date	Generator Hours	Maintenance Performed

Duro Max

Checking the Oil



Check the oil

The generator is equipped with an automatic shutoff to protect it from damage due to low oil; nonetheless, you should check the oil level of the engine before each use to ensure that the engine crankcase has a sufficient amount.

To check the oil level:

- a. Make sure the generator is on a level surface.
- b. Pull out dipstick.
- c. With a dry cloth, wipe the oil off of the dipstick.
- d. Insert the dipstick as if you were replacing it and then remove it again. There should now be oil on the stick. If there is no oil on the stick, or oil only at the very end of the stick, you should add oil until the engine crankcase is filled (see “Adding Oil” portion of the “Maintenance” section).
- e. Be sure to replace the dipstick when finished checking oil.

Model Number	XP28000iH
Engine Oil Capacity	84.5 fl. oz. (2.5 L)

Changing the Oil



CAUTION: Worn out or dirty oil does not cool the generator properly and can lead to catastrophic engine damage.

In addition to regular oil changes, it is necessary to drain the oil from the crankcase if it has become contaminated with water or dirt.



1. Remove right service cover

Remove the right service cover, then locate the oil drain hose, which is located on the bottom of the engine block.



2. Remove oil drain cap

Place oil drain into an approved oil disposal container, then unscrew the oil drain cap.



3. Drain oil

Allow oil to drain into an approved oil disposal container. Contact your local auto parts store for information on oil disposal.



4. Replace oil drain cap

After oil has fully drained, screw the oil drain cap back on.



5. Remove left service cover

Remove the left service cover to allow access to the oil filter.



6. Replace oil filter

Unscrew old oil filter, then replace with new oil filter. Note: During installation of new oil filter place a small amount of oil around the oil filter gasket before screwing the new filter on.



7. Add new oil

Remove oil cap and add new oil to engine.

Cleaning the Air Filter

MAINTAIN AIR FILTER

Clean air filter after every 50 hours of use
(every 10 hours in unusually dusty conditions)

Wash filter element with household detergents.
Wipe out dust from air filter housing before
replacing filter element.

Never clean with a brush

Routine maintenance of the air cleaner helps maintain proper airflow to the carburetor. Check that the air cleaner is free of excessive dirt after every use.



CAUTION: Improper maintenance may cause less air to enter the engine or dirty air to enter the engine causing overheating and engine wear.



1. Remove right service cover

Remove the right service cover, then locate the air filter cover that's on top of the engine.



2. Unclip air filter cover

Unclip both sides of the air filter cover and remove the air filter cover.



3. Remove air filter element

Remove air filter element and inspect. If element appears dirty or worn, then replace as needed.



4. Replace element in air filter

Replace air filter element into air filter casing.



5. Replace air filter cover

Replace the air filter cover and fasten clips.

Spark Plug Maintenance



The spark plug is important for proper engine operation. A good spark plug should be intact, free of deposits, and properly gapped. Please note there are 2 spark plugs on this generator model that are located behind each service panel.



CAUTION: Improper maintenance may cause reduced fuel economy, misfires, trouble starting, or damage to the spark plug threads.



1. Remove spark plug cap

Pull on the spark plug cap to remove it.



2. Remove spark plug

Unscrew the spark plug from the generator using a socket wrench.



3. Inspect spark plug

Visually inspect the spark plug. If it is cracked or chipped, discard and replace it with a new spark plug. We recommend using a Torch F7RTJC.



4. Measure plug gap

Measure the plug gap with a gauge. The gap should be 0.7-0.8 mm (0.028-0.031 in).



5. Clean and re-gap

If you are re-using the spark plug, use a wire brush to clean any dirt from around the spark plug base and then re-gap the spark plug.



6. Install spark plug

Screw the spark plug back into its place on the generator using the spark plug wrench.



7. Replace spark plug cap

Replace the spark plug cap.

Transporting the Generator



1. Empty the gas tank

Fully drain your gas tank using a fuel siphon.



2. Disconnect the spark plug

Pull on spark plug cap to disconnect spark plug from ignition wire.



CAUTION: Do not obstruct any ventilation openings and keep the generator in a cool dry area.




CAUTION: Never place any type of storage cover on the generator while it is still hot.

Storing the Generator for Use Within 30 Days




1. Add fuel stabilizer to gas tank

Add fuel stabilizer to gas tank to help preserve gasoline for longer storage period.



2. Flip main breaker OFF and run

Turn OFF the main breaker and allow the generator to run for 3-5 minutes.



3. Flip start switch OFF/Store

Flip the start switch to the OFF position and store the generator.



CAUTION: Do not obstruct any ventilation openings and store the generator in a cool dry area.



CAUTION: Never place any type of storage cover on the generator while it is still hot.


MAINTENANCE AND CARE (CONTINUED)

Storing the Generator for Longer Than 30 Days




1. Add fuel stabilizer to gas tank

Add fuel stabilizer to gas tank to help preserve gasoline for longer storage period.




2. Flip main breaker OFF and run

Turn OFF the main breaker and allow the generator to run for 3-5 minutes.



3. Flip start switch OFF

Flip the start switch to the OFF position.




4. Empty the gas tank

Fully drain your gas tank using a fuel siphon.




5. Remove spark plug

Remove spark plug as shown in “Spark Plug Maintenance” on page 68.



6. Add oil to cylinder

Add 2 tablespoons of 10W-30 motor oil directly into the spark plug hole on each side, and pull the recoil to lubricate cylinder. After lubricating cylinder reinstall the spark plug.



7. Remove battery and charge

Remove the generator battery and place it on a 12V battery tender indoors.

SPECIFICATIONS

Model Number	XP28000iH
AC Rated Wattage (Gasoline)	22,000 W
AC Rated Wattage (Propane)	20,000 W
AC Surge Wattage (Gasoline)	28,000 W
AC Surge Wattage (Propane)	25,000 W
AC Rated Voltage	120/240V
Dimensions	39.25"L x 31"W x 34.5"H
Weight	466 lbs
Recommended Oil	10W-30
Engine Displacement	999 cc
Gasoline Capacity	12.7 US gal.
Oil Capacity	84.5 fl. oz. (2.5 L)
Bore	90 mm
Stroke	78.5 mm
Engine Speed	3400 rpm
Oil Cooling Type	Pressure and splash
Bearing Type	6003 Sliding bearing
Cylinder Sleeve	Cast iron sleeve
Fuel Delivery System	Carburetor
Valve Type	OHV
Engine Type	4-Stroke
Engine Cooling Type	Forced air
Run Time @ 25% (Gasoline)	16 hr.
Run Time @ 25% (Propane)	18 hr. (60 lb.)
Starting Type	Electric
Noise Level	70 dB @ 25% load
Neutral System	Bonded
AC Rated Frequency	60 Hz
AC Phase	Single
Winding Material	100% copper windings
Suggested Propane Tank Size	60 lbs. minimum



TROUBLESHOOTING

This section of the manual is to help you troubleshoot problems with your generator.

Duro Max

Mode	Description	Solution
Engine will not start	Battery not charged	Charge battery
	Engine switch is in the "OFF" position	Turn engine switch to the "ON" position
	Stale gasoline or water in gaso- line	Drain entire system and refill with fresh fuel
	Engine is out of fuel	Add fuel
	Fuel is old or contaminated	Change fuel
	Spark plug is dirty	Clean spark plug
	Spark plug is broken	Replace spark plug
	Generator is not level	Move generator to a level surface
	Oil is low	Add/Change oil
Engine runs, but there is no electrical output	Circuit breaker is "OFF"	Turn "ON" circuit breaker
	Wiring connection is bad	Replace extension cord(s)
	Device connected to generator is malfunctioning	Disconnect malfunctioning device
Generator runs, but does not support all electrical devices connected	Generator is overloaded	Disconnect 1 or more items to reduce the load
	Device connected to generator is bad	Disconnect malfunctioning device
	Air cleaner is dirty	Clean/Replace the air filter

WARRANTY

5-year Warranty

All DuroMax Power Equipment warrant the original purchasers to a 5-year Parts Warranty (Residential Use ONLY: Unusually heavy or commercial use is covered for a period of 1-year) in the event of failure due to defects in electrical or mechanical components. Freight on any items submitted for replacement or repair under the Warranty is the responsibility of the equipment owner. This warranty is non-transferable and only valid to the original purchaser.

Warranty Exclusions

The DuroMax Power Equipment warranty does not cover repairs or returns when the fault is: Normal Wear and Tear, Installation Use or Maintenance Services, Cosmetic defects, Accessories, Failures due to acts of God or Natural Disasters, or problems related to/from aftermarket or non-OEM parts.

Warranty Limitations

DuroMax Power Equipment does not claim or hold any obligation to loss of time, freight charges, use of the product, or any incidental damages from the use of this product. THIS WARRANTY IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED.



YOUR WARRANTY RIGHTS AND OBLIGATIONS

The United States Environmental Protection Agency and DuroMax Power Equipment, are pleased to explain the emission control system warranty on your 2025/2026 model year small off-road engine/equipment. In the United States, new small off-road engine/equipments must be designed, built and equipped to meet stringent anti smog standards. DuroMax must warrant the emission control system on your small off-road engine/equipment for the periods of time listed below provided there has been no abuse, neglect or improper maintenance of your small off-road engine/equipment.

Where a warrantable condition exists, DuroMax will repair your small off-road engine/equipment at no cost to you including diagnosis, parts and labor.

MANUFACTURER'S WARRANTY COVERAGE:

This emissions control system is warranted for two years. If any emission-related part on your small off-road engine/equipment is defective, the part will be repaired or replaced by DuroMax.

OWNER'S WARRANTY RESPONSIBILITIES:

As the small off-road engine/equipment owner, you are responsible for the performance of the required maintenance listed in your owner's manual. DuroMax recommends that you retain all receipts covering maintenance on your small off-road engine/equipment, but DuroMax cannot deny warranty solely for the lack of receipts or for your failure to ensure the performance of all scheduled maintenance.

As the small off-road engine/equipment owner, you should however be aware that DuroMax may deny you warranty coverage if your small off-road engine/equipment or a part has failed due to abuse, neglect, improper maintenance or unapproved modifications.

If you have any questions regarding your warranty rights and responsibilities, you should contact DuroMax at 844-387-6629 or support@duromaxpower.com.

DEFECTS WARRANTY REQUIREMENTS:

(a) The warranty period begins on the date the engine/equipment is delivered to an ultimate purchaser.

(b) General Emissions Warranty Coverage. DuroMax warrants to the ultimate purchaser and each subsequent owner that the engine/equipment is:

(1) Designed, built, and equipped so as to conform with all applicable regulations adopted by the Environmental Protection Agency.

WARRANTY (CONTINUED)

(2) Free from defects in materials and workmanship that causes the failure of a warranted part for a period of two years.

(c) Warranty Parts for Exhaust Emission.

- (1) Fuel System
- (2) Air Induction System
- (3) Ignition System

The following parts are also considered emission related components for exhaust emissions, if applicable

- (1) Exhaust Gas Recirculation (EGR) System
- (2) After treatment devices.
- (3) Crankcase ventilation valves.
- (4) Sensors.
- (5) Electronic control units.

(d) Warranty Parts for Evaporative Emission include fuel tank, fuel cap, fuel line and fittings, carbon canister, vapor hoses. They may also include, if applicable, liquid/vapor separator, clamps, pressure relief valves, etc.

DuroMax will furnish with each new engine/equipment written instructions for the maintenance and use of the engine/equipment by the owner.

CUSTOMER SERVICE DEPARTMENT

DuroMax Power Equipment is committed to ensuring that our products perform when they need to. Our generators are your lifeline in the event of an emergency. Should you have any problems, please contact our customer service department:

DUROMAX POWER EQUIPMENT
5800 Ontario Mills Parkway
Ontario, CA 91764

Customer Service: 844-DUROMAX
Customer Service Hours: 8-5 pm PST Mon-Fri

Website: www.duromaxpower.com
Email: customerservice@duromaxpower.com





5800 Ontario Mills Parkway
Ontario, CA 91764
United States

844-DUROMAX



XP28000iH-MANUAL

REV: XP28000iH-07182025