Charging Instructions

1.Charge in a well-ventilated space between 10°C and 30°C (50°F–86°F), avoiding direct sunlight, heat sources, and temperature extremes.
2.Before using for the first time, please charge the device and leave it charging for an additional 2 hours after all green indicator lights on the charger turn on.
3.Avoid overcharging, undercharging, and over-discharging the battery. When daily discharge is shallow (less than 10% of total capacity or continuous range), daily charging is not required. The battery should be sufficiently discharged and promptly recharged periodically (such as every 1 to 2 months) to maintain its capacity and avoid shortening battery life.
4.The battery should be charged using the original charger. Once the battery is fully charged, do not leave it charging for an extended period to avoid overcharging and water loss.
5.When charging, first connect the charger to the vehicle socket, then plug it into the power outlet. Once charging is complete, disconnect from the power outlet first, then remove the charger from the vehicle socket.

Operating Guidelines

1.Please use the product within a temperature range of -10°C to 35°C (14°F–95°F).
2.Avoid deep discharge. It is recommended to recharge promptly when battery capacity usage exceeds 70% or when over 70% of the total continuous range is reached.
3.Keep the battery surface, connecting cables, and terminals dry and clean. Regularly inspect terminals for looseness, and promptly remove any oxidation on the terminals and connectors.
4.If you experience a sudden drop in range or a noticeable decline in discharge performance during use, promptly inspect the charger, motor, and battery, and contact BougeRV customer service.

Storage Guidelines

1.The optimal battery storage temperature is between 5°C and 35°C (41°F–95°F). Ensure the storage environment is dry, clean, and well-ventilated, and keep away from direct sunlight, heat sources, flammable or explosive materials, and chemicals.
2.When the product is not in use for an extended period, the battery should be fully charged before storage and fully recharged once a month.