



OWNER’S MANUAL

Safety Information

- Do not expose the device to liquids or moisture.
- Clean only with a dry cloth.
- Do not use near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers).
- Do not defeat the safety purpose of the polarized or grounding-type plug.
- Protect the power cord and pedal cables from being walked on or pinched.
- Only use the original attachments and accessories specified by Ibanez.
- During lightning storms or when unused for long periods of time, please unplug.
- Do not attempt to service the device by yourself, as opening or removing cover may expose you to dangerous voltage or another hazard.
- Servicing is required when the unit has been damaged in any way, such as a power cord or plug is damaged, liquid has been spilled or objects have fallen into the unit, the unit has been exposed to rain or moisture, does not operate normally, or has been dropped.
- Never push any object into the slots or openings on your unit enclosure.
- When connected to a power outlet, power is always flowing into your unit. To totally disconnect power, unplug the power cord.

Operation

DC Power input

Needs DC15-25V. Connect to the included AC/DC adapter. We have tested the operation with the included adapter. We cannot guarantee operation with other adapters.

Power output port 1-3

Each 2.1mm jack supplies 9V/500mA (max.).

Power output port 4-5

Adjustable voltage ports. Each 2.1mm jack supplies at the following toggle switch positions.

- Up: 18V/150mA (max.)
- Middle: 12V/225mA (max.)
- Down: 9V/300mA (max.)

Power output port 6

2.1mm jack supplies 9V/300mA (max.).

LED Indicator

- A) Off: No DC cable connection.
- B) Green: A DC cable is connected and the output works properly.
- C) Green flash: Connection has an error. (Error: e.g., short, overload)



Notice

- The polarity of all the ports are center-negative.
- Make sure the power supply voltage and current consumption (or total current consumption in case of daisy-chain connection) of the connected devices and make sure the current consumption will not exceed the maximum output current of each port.
- Current doubler connection for a long time is not recommended because one port could be overloaded, in which case the surface of the Power Stoke enclosure could get too hot.

Bundled items

- 1 × AC/DC adapter (Input: AC100-240V, Output: DC15V)
- 1 × IEC power cord
- 3 × Ibanez DCT twisted DC cable (8"/20cm)
- 3 × Ibanez DCT twisted DC cable (16"/40cm)
- 4 × 3M Dual Lock™ fastener tape
- 4 × rubber foot

Specification

- 15-24V DC input with anti-reverse connection
- Full-isolated 6 output ports
- 3 × 9V/500mA port
- 2 × adjustable voltage port (9V/300mA, 12V/225mA, 18V/150mA)
- 1 × 9V/300mA port
- Max. output power: 21.6W in total
- Dimensions: 92mm(L) x 88mm(W) x 29mm(H), 3.6"(L) x 3.5"(W) x 1.2"(H)
- Weight: 180g, 0.40 lbs

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) This device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instruction, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determine by turning the equipment off and on, the user is encouraged to try to correct the interference by one of more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

To maintain compliance with FCC's FR Exposure guidelines, this equipment should be installed and operated with minimum distance between 20cm the radiator your body: Use only the supplied antenna.



HOSHINO GAKKI CO., LTD.
No.22, 3-Chome, Shumoku-Cho,
Higashi-Ku, Nagoya, Aichi, JAPAN





取扱説明書

⚠ 安全上のご注意 ⚠

- 液体や湿気で濡らさないでください。
- 機器を拭くときは乾いた布をお使いください。
- 火や暖房機器の近く、直射日光の当たる場所等、熱を発する物の近くや場所で使用しないでください。
- 電源コードや DC ケーブルを強く挟んだり足で踏むことが無いよう設置してください。
- 付属の電源アダプター以外は使用できません。
- 雷が鳴るときや長時間使用しないときは電源コードを抜いてください。
- ご自身で修理しようとししないでください。筐体を開けると感電・火災・故障の原因になり得ます。
- 電源コードやプラグが破損している、液体をこぼした、物を落とした、雨や湿気にさらされた、正常に動作しない、落下したなど、何らかの形で機器が損傷した場合は、修理が必要です。
- 機器の内部に異物を入れないでください。
- コンセントに接続されているとき、電源は常に機器に供給されています。電源を完全に切断するには、電源コードを抜いてください。

操作方法

1 電源入力

直流 15-25V が必要です。同梱の AC/DC アダプターを繋いでください。同梱のアダプターで動作確認を行っております。他のアダプターをお使いの場合の動作保証はいたしかねます。

2 出力ポート 1-3

それぞれの 2.1mm ジャックから 9V/ 最大 500mA が供給されます。

3 出力ポート 4-5

可変電圧ポートです。それぞれの 2.1mm ジャックは下記トグルスイッチの位置によって出力電圧を変えることができます。

- 上：18V/ 最大 150mA
- 中：12V/ 最大 225mA
- 下： 9V/ 最大 300mA

4 出力ポート 6

2.1mm ジャックから 9V/ 最大 300mA が供給されます。

5 LED インジケーター

- A) オフ： 無接続
- B) 緑： ケーブルが接続されており、正常に動作しています。
- C) 緑点滅： ケーブルが接続されていますが、異常があります。(ショート、過負荷等)



ご注意

- 全てのポートの極性はセンターマイナスです。
- 接続する機器の電源電圧と消費電流（デジチェーン接続をする場合は合計の消費電流）をよくお確かめのうえ、各ポートの最大出力電流を超過しないようにしてください。
- 長時間でのカレントダブラー接続は、片側のポートの負荷が高くなる可能性があり、その場合 Power Stoke の筐体表面が熱くなりすぎる恐れがあるため、推奨しておりません。

付属品

- 1 × AC/DC アダプター（入力：AC100-240V、出力：DC15V）
- 1 × IEC 電源コード
- 3 × Ibanez DCT ツイスト DC ケーブル (8"/20cm)
- 3 × Ibanez DCT ツイスト DC ケーブル (16"/40cm)
- 4 × 3M Dual Lock™ 面ファスナー
- 4 × ゴム足

仕様

- 直流 15-24V 入力 逆極性入力保護付き
- フルアイソレーテッド出力ポート
- 3 × 9V/500mA ポート
- 2 × 可変電圧ポート (9V/300mA, 12V/225mA, 18V/150mA)
- 1 × 9V/300mA ポート
- 最大出力電力：合計 21.6W
- 寸法：92mm(L) × 88mm(W) × 29mm(H)、3.6"(L) × 3.5"(W) × 1.2"(H)
- 重量：180g, 0.40 lbs

- DEUTSCH / BEDIENUNGSANLEITUNG
- FRANÇAIS / MANUEL DE L'UTILISATEUR
- ESPAÑOL / MANUAL DEL USUARIO
- ITALIANO / MANUALE D'ISTRUZIONI
- NEDERLANDS / GEBRUIKERSHANDLEIDING
- PORTUGUÊS / MANUAL DO PROPRIETÁRIO
- POLSKI / INSTRUKCJA OBSŁUGI
- РУССКИЙ / РУКОВОДСТВО ПОЛЬЗОВАТЕЛЯ



<https://www.hoshinogakki.co.jp/pdf/ibanez/manual/de/electronics/PWRS6.pdf>